



Reinstallation/Resetting Procedure of Dream Satellite TV IRD Boxes

For digi-all world Units, NOKIA, Vistar, HomeCas and DAW(old software):

HOMECAS IRD BOX

01. MENU
02. Installation
03. Press OK (password can be "1234")
04. Automatic Search
05. Press OK
06. Will Scan Channels
07. Press Exit
08. Will prompt "If You Want To Save Updated Channels..." select YES
09. End of procedure.

NOKIA IRD BOX

01. On your Remote Control, select MENU
02. Select SETTINGS by pressing the right arrow button
03. Press the up arrow button to SYSTEM CONFIGURATION
04. Enter your ACCESS CODE (1234)
05. Select Re-Install, then press OK (a warning will appear, just press OK)
06. When the Remote Control appears on the screen, press OK
07. Antenna Conf., receiver LNB Type - UNIVERSAL, press OK
08. Automatic Search, press OK
09. If the Signal Strength or Signal Quality is higher than 50%,
press OK to begin Channel Search...
10. You should get 38 TV Channels and 10 Audio Channels to complete the
installation.
(If not, just repeat the process)
11. Time Adjustment, press OK, Welcome Installation completed, press OK
12. Adjust Volume.
13. End of procedure.

DAW IRD BOX (Software Version 7.1 or 8.2)

01. On your Remote Control, select MENU
02. Go to INSTALLATION, enter Access Code, press OK
03. Go to FACTORY RESET, press OK
04. YOU HAVE TO DO THE FIRST INSTALLATION TO FIND CHANNELS, press OK
05. Under EQUIPMENT, go to NONE, press OK
06. Press SUB.T button (RED BUTTON) on your Remote Control
07. CHANNEL SEARCH, then it will start to SAVE CHANNELS, press OK
08. IF YOU WANT TO SAVE ALL SCANNED CHANNEL INFO, press OK
09. Confirmation, "SAVED" will appear, press OK
10. Will go back to Channel Search Screen, press EXIT, will go to Channel 1
11. ADJUST VOLUME
12. End of procedure.

VISTAR IRD BOX

01. Press MENU
02. Select SYSTEM CONFIGURATION
03. Enter PASSWORD (Default is 1234)
04. Select FACTORY DEFAULT
05. Enter PASSWORD (Default is 1234)
- "Do you want to reset the receiver? The access code reset to default?"
06. Press OK (wait for about 5 seconds)
07. Will display WELCOME; press OK to continue
08. Will display LNB CONFIGURATION; check specifications as follows:
 - ANTENNA 1
 - SATELLITE Default 01
 - LNB TYPE Universal
 - LNB POWER Yes
 - LNB LOW FREQ. (kHz) 9750000
 - LNB HIGH FREQ. (kHz) 10600000
 - DISEqC / TONE BURST Disable
09. Press OK
10. Will display ADD CHANNELS; check specifications as follows:
 - (Signal Strength about 50%; Signal Quality above 75%)
 - SATELLITE Default
 - TRANSPONDER TP1
 - FREQ. (kHz) 12301000
 - SYMBOL RATE 25600
 - 0 / 22 kHz ON
 - POLARIZATION 18V
 - SEARCH TYPE Network
11. Press OK (SEARCH CHANNEL)
 - "Searching In Process, Please Wait..."
12. Will display 38 Digital TV Channels; 10 Radio Channels
13. Press OK to complete the procedure.

DAW IRD BOX (with Old Software)

01. Press MENU, select INSTALLATION, press OK
02. Enter ACCESS CODE (1234), then press OK
03. Got to Factory Reset, press OK to confirm
04. The screen will display "You Must Do
The First Installation To Find Channels", press OK
05. SEARCH MODE (press LEFT or RIGHT ARROW button key) to
change from AUTO to MANUAL, press OK
06. Manual Search Screen, select POLARITY (press LEFT or RIGHT ARROW key) to
change from VERTICAL to HORIZONTAL
07. Press OK to Start Channel Search.
08. Total TV (38) and Radio (10) Channels will appear.
09. Wait until screen goes back to Manual Search. Press OK to complete the
installation.
10. End of procedure...